

ELECTRONIC DISPLAYS INC.

135 S. CHURCH STREET
ADDISON, ILL. 60101

www.electronicdisplays.com



EDV300 – 115 – 8D – N1



Parts List:

- EDV300 display with power adapter
- IR remote

Qty: 1
Qty :1

Infrared Remote (IR) Overview – Version 2



Power Button - Turns display ON or OFF



Increases Brightness of display

Decreases Brightness of display



Remove Negative increment value icon

Sets Negative increment value icon



Enters Display Configuration



Edits values in display configuration



Removes leading zeros

Display controls

Start Button

Stop Button

Reset Button



Display Configuration

Preset Display

1. Press the **EDIT** button.
2. Change the value of the flashing digit using the number buttons on the remote. Use the left or right arrow button to move to another digit.
3. Press the **ENTER** button to save the value on the display.

Set Increment Interval and Value

1. Press the **DEL** button. The current Increment Interval (in seconds) will be displays in the left four digits. The current Increment Value will be in the right three digits.
 2. Press the **EDIT** button to edit the values displayed. Use the right and left arrows to navigate through the display's digits.
 3. Press the **ENTER** button to save the value on the display.
- **Note:** The display is limited to a 4 digit increment interval, meaning the largest increment interval that can be set is 9999 seconds or every 166.65 minutes

Set display to Time Up/Down

1. Press the **DEL** button to enter Setup Mode.
2. To set a Negative increment interval (**Time Down**):
 - Press and Hold the Down arrow in the TIMER1 section of the remote until a negative sign appears in the fourth digit.
3. To set a Positive increment value (**Time Up**):
 - Press and hold the Up arrow in the TIMER1 section of the remote until there is no negative sign in the fourth digit.
4. Press the **DEL** button to save and exit Setup Mode.

Display Brightness

Use the TIMER2 arrows to change the display brightness

- UP arrow increases brightness
- DOWN arrow decreases brightness

Notes on Display Operation

- Use the Start, Stop and Reset buttons to control the display (see the "Display Controls" section on the previous page).
- The display counts up until 99,999,999; it does not roll over to zero.
- The display counts down until 0; it does not display negative values.
- Leading zeros on the display can be removed by pressing the Zero button when not in Setup Mode.

Please visit our website for more information:

www.electronicdisplays.com

Or Call: 1-800-367-6056

Or Our Support Website:

<http://edisupport.helpserve.com/>