

ELECTRONIC DISPLAYS INC.

135 S. CHURCH STREET
ADDISON, ILL. 60101
www.electronicdisplays.com

1-800-367-6056



EDV225MPC-2L-N1-GR-IR



Parts List:

- | | |
|----------------------------|--------|
| • EDV225MPC-2L-N1-GR-IR | Qty: 1 |
| • IR remote | Qty :1 |
| • Photo-Eye with Reflector | Qty :1 |

Programming the display

To preset a value to the display, follow the guide below for the line that you want to set.

Target / Goal:

1. Press the **TIME** button to enter edit mode. The least significant digit's decimal point will flash on and off.
2. Press the **DEL** button on the remote to remove the current value in the least significant digit (value will shift to the right).
3. Input the desired numeric value.
4. Press **OK** when complete.

Note: If the incorrect value is displayed on the screen, press the **F2** button on the remote.

Actual:

1. Press the **SET** button to enter edit mode. The least significant digit's decimal point will flash on and off.
2. Press the **DEL** button on the remote to remove the current value in the least significant digit (value will shift to the right).
3. Input the desired numeric value.
4. Press **OK** when complete.

Changing increment value (Actual line)

1. Press the **F2** button. Display will show the current increment value with a decimal point.
2. Press the **DEL** button to remove the current value.
3. Input the desired increment value
4. Press **OK** when complete.

Photo-Eye setup

The display includes a Photo-Eye and a reflector. The Reflector must be mounted directly across from the Photo-Eye in the direction that it is pointing.

The photo-Eye emits an infrared beam that reflects off the reflector plate. Each time that the beam is broken, the Actual line on the display will increment.

Please visit our website for more information:

www.electronicdisplays.com

Or Call: 1-800-367-6056

Or Our Support Website:

<http://edisupport.helpserve.com/>