

ELECTRONIC DISPLAYS INC.

135 S. CHURCH STREET

ADDISON, ILL. 60101

www.electronicdisplays.com

1-800-367-6056



Specialists in Information Displays

www.ElectronicDisplays.com

EDV225MPC-2L-N1-GR-IR



Parts List:

- EDV225MPC-2L-N1-GR-IR
- IR remote
- Photo-Eye with Reflector

Qty: 1

Qty :1

Qty :1

To configure the display using the IR remote follow these instructions. The “SET” button will be used to edit both lines. Keep pressing “SET” to rotate through the edit mode.

Preset Top Line (TARGET)

Enter the **EDIT** mode

1. To edit the top line, point the IR remote toward the center of the display. Press the “SET” button until the LED dot in the lower right corner of the least significant digit flashes.
2. Enter the number you want displayed. Press “SET”.

Preset Bottom Line (ACTUAL)

Enter the **EDIT** mode

1. To edit the bottom line, point the IR remote toward the center of the display. Press the “SET” button until the LED dot in the lower right corner of the least significant digit flashes.
2. Enter the desired preset numbers
3. Press the “SET” button to save

Change Increment value (Top Line)

1. Press the “SET” button until the top line shows “00.00” . Display will show current time increment duration. **It is set at the factory as a non-incrementing number.**
2. Press the “SET” button until the current value is removed. Input the desired time duration (in Seconds) and press “SET” to complete. **For example, top increment every “15” seconds, press “150”. The display will show 15.0**
3. Press the “SET” button once again. The **GOAL** line decimal point will flash to show the display is now running.
4. Input desired Increment value through the remote.
5. Press the “SET” button to save

You may also manually increase or decrease the counter by using the IR remote. Press the ‘Up’ arrow to increase the counter by one step or press the ‘Down’ arrow to decrease the counter by one step.

Notes

A photo-eye and reflective plate are provided with the sign. The reflective plate needs to be installed in the direction the photo-eye is being pointed at. The photo-eye operates by sending an infrared beam in the direction that it is being pointed. The plate will reflect the IR beam back to the photo-eye thus incrementing the bottom line of the display. Each time the beam is broken, the bottom line will increment by one.

Terminal Block



A 'Clear' terminal block has been added to the EDV225MPC-2L-N1-GR-IR. A contact closure between the two terminals will reset the second (Actual) line of the display. Reset occurs after contact between the two terminals is released.

Please visit our website for more information:

www.electronicdisplays.com

Or Call: 1-800-367-6056

Or Our Support Website:

<http://edisupport.helpserve.com/>