

ELECTRONIC DISPLAYS INC.

135 S. CHURCH STREET
ADDISON, ILL. 60101

www.electronicdisplays.com

1-800-367-6056



EDI
Specialists in Information Displays

www.ElectronicDisplays.com



ED400MSC-E-2F-N4

This display will increment by "1" every 24 hours automatically.
To configure the display using the IR remote follow these instructions:



Display Programming

1. **To set the top line: Press the “F-A” button.** The top line will flash.
2. **To set the bottom line: Press the “C-U” button.** The bottom line will flash.
3. Enter the number of days (DDDD) you would like to increment from using the numeric section of the remote. Press the **ENTER** button when desired value set

DDDD

DDDD = Days saved on display

4. To start incrementing by one every 24 hours. Input the current hours (HH) in a 24-hour format. Press the **ENTER** button to set.

1 - HH

HH = Hours saved on display

1. Input the current hours (MM) in a 2-digit format. Press the **ENTER** button to set.

2 - MM

MM = Minutes saved on display

5. Input the current Seconds (SS) in a 2-digit format. Press the **ENTER** button to set.

3 - SS

SS = Seconds saved on display

5. Set the display to increment. Press the **“START”** button. **The display will briefly flash.** You are now programed to increment by “1” every 24 hours from the preset time.

Brightness Control

○ Press the “EXIT” button to increase brightness. Stop at desired setting

Note: Brightness can only be set when not in edit mode.

Please visit our website for more information: www.electronicdisplays.com
Or Call: 1-800-367-6056 / Our Support Website: <http://edisupport.helpserve.com/>